



VHF AND UHF TRANSCEIVERS

IC-F3162T

(UHF transceiver with 10-keypad)

IC-F4162T

(UHF transceiver with 10-keypad)

IC-F3162S

(UHF transceiver without 10-keypad)

IC-F4162S

(UHF transceiver without 10-keypad)



iDAS

ICOM DIGITAL ADVANCED SYSTEM



Complete Analog Conventional IDAS Digital



- 512 ch / 128 zones
- Conventional/BIIS 1200 mode
- IDAS digital (With UT-126H)
- 2-Tone, 5-Tone CTCSS, DTCSS
- VHF 5W, UHF 5W output
- 14 hrs. operating time with BP-232N
- Full dot-matrix LCD

ADVANCED TECHNOLOGY FOR THE FUTURE



▲ IC-F3162T

▲ IC-F4162S

VHF TRANSCEIVERS

IC-F3162T

With 10-keypad

IC-F3162S

Without 10-keypad

UHF TRANSCEIVERS

IC-F4162T

With 10-keypad

IC-F4162S

Without 10-keypad

IP55 Dust-protection and water jet resistance

The IC-F3162 series meets IP55 requirements for dust-protection and water jet resistance. Its durable construction is backed up by the aluminum die-cast chassis and polycarbonate casing, allowing reliable operation under harsh weather and environmental conditions.

Lithium-Ion battery pack

The supplied 2000mAh Li-Ion battery pack, BP-232N, provides 14 hours* of operating time. Icom's rugged dual-rail guide securely locks the battery to the radio. The optional battery case BP-240 provides a convenient back up and great reassurance in an emergency.

* Typical operation Tx:Rx:Stand-by=5:5:90, power save on

Most popular signalings built-in

The 2-Tone, 5-Tone, CTCSS, DTCS and BISS signaling capabilities are built-in for group communication or selective calling. Also, the IC-F3062 series can decode ten 2-Tone codes or eight 5-Tone codes on a channel. When a matched tone is received, the following actions are programmable for each code.

- Beep sound
- Bell icon
- Auto TX
- Answer back call
- Scan
- Radio stun/kill/revive

Wide frequency range and large channel capacity

The IC-F3162 series covers a wide frequency range in one version (VHF 136–174 MHz, UHF 400–470MHz). The 512 memory channel capacity with 128 zones allows you to divide and store a variety of flexible channel groupings. Memory channel selection can be made with a simple rotation of the rotary channel knob. Wide, middle and narrow channel bandwidth (25/20/12.5kHz)* is also programmable.

* Programmable 25/12.5kHz or 20/12.5kHz

Voting mode scanning

The Voting mode scanning detects the S-meter level of repeater stations and automatically selects the strongest station, useful for roaming between 2 or more repeater sites. Once you program the voting mode to a memory zone, you can easily start voting mode operation by changing the zone setting.

UTURE NOW!

Full dot-matrix LCD

Using a large full dot-matrix LCD (32 × 18 mm), the IC-F3162 series shows upper and lower case characters clearly. The display setting is selectable from 1 line, 12 characters or 2 lines 24 characters via programming. The bottom row shows assigned functions to the [P0] to [P3] buttons.



Enhanced audio

The IC-F3162 series employs a BTL amplifier that increases the audio output and the built-in audio compander provides clear, low noise communications.

Built-in inversion-type voice scrambler

The built-in inversion type voice scrambler* provides secure conversation as standard. When a more secure system is required, optional voice scrambler UT-109R or UT-110R are available.

* Inversion type voice scrambler is not compatible with UT-109/UT-110 voice scrambler.

BIIS 1200 compatible

The following selective calling and data features are available with the built-in BIIS system.

- 32 abbreviated call memories
- 7 group IDs • 24-status Messages
- Send 12-character SDM (Short Data Message)
- Receive up to 95 characters of free text
- GPS position reporting function with optional HM-170GP

Other features

- Built-in basic LTR™ trunking capability.
- 8 DTMF autodial memories
- 2 step reduced power setting
- Power on password
- Busy, repeater lockout functions
- Surveillance function temporarily turns off the LED backlight and beep sound
- Powerful 5W output both VHF and UHF
- Flash CPU for future upgrade and more...

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.

BATTERY PACKS AND CASE

▲ BP-230N ▲ BP-232N ▲ BP-240

Battery packs	Type and capacity	Operating time*	Output power
BP-230N	Li-Ion 7.4V/ 980mAh	7.35 hours	5W
BP-232N	Li-Ion 7.4V/2000mAh	14 hours	5W
BP-240	AAA (LR03) batteries × 6	—	1W

* Operating time is approximate time (at 20°C). Tx: Rx: standby=5:5:90. Power save on.

REGULAR CHARGER

▲ BC-147 ▲ BC-171

BC-171 DESKTOP CHARGER + BC-147 AC ADAPTER
Charges the battery pack in 8–10 hours (approx.).

RAPID CHARGER

▲ BC-145 ▲ BC-160

BC-160 DESKTOP CHARGER + BC-145 AC ADAPTER
Charges the BP-232N in 3 hours (approx.).
BC-119N + AD-106 + BC-145 is also available.

POWER SUPPLY CABLES

▲ CP-17L ▲ OPC-515L

CP-17L CIGARETTE LIGHTER CABLE, OPC-515L DC POWER CABLE
For use with the BC-160 or BC-119N. (12–16V DC required).

MULTI-CHARGER

▲ BC-121N+AD-106 (6 pcs.) ▲ OPC-656 ▲ BC-157

BC-121N MULTI-CHARGER + AD-106 CHARGER ADAPTER + BC-157 AC ADAPTER
Rapidly charges up to 6 battery packs (Six AD-106s are required). Charging time: 3 hours (approx.) when BP-232N is attached.
OPC-656 DC POWER CABLE :For use with the BC-121N. (12–20V DC required).

BELT CLIPS AND LEATHER BELT HANGERS

▲ MB-93 ▲ MB-96F

MB-93 : Swivel type belt clip.
MB-94 : Alligator type. Same as supplied.
MB-96N : Swivel type belt hanger.
MB-96F : Fixed type belt hanger.

SPEAKER-MICROPHONES

IPX7 IP57 GPS IP57

HM-168 HM-169 HM-170GP HM-159SC

HM-168: Compact type speaker-microphone. Equivalent to IPX7.
HM-169: Rugged type speaker-microphone. Equivalent to IP57.
HM-170GP: GPS speaker-microphone. Equivalent to IP57.
HM-159SC: Full size durable speaker microphone with revolving clip.
HM-131SC: Compact type speaker microphone.

INTERNAL UNITS

UT-109R UT-110R UT-124R UT-126H

UT-109R: Non-rolling type voice scrambler.
UT-110R: Rolling type voice scrambler.
UT-124R: Man down unit. Automatically sends an emergency signal when the transceiver is left in a horizontal position for a preset time.
UT-126H: IDAS Digital unit.

HEADSETS AND PTT/VOX UNIT

HS-94 HS-95 HS-97 VS-1SC

HS-94: Earhook headset with flexible boom microphone.
HS-95: Behind-the-head headset with flexible boom microphone.
HS-97: Throat microphone fits around your neck and picks up speech vibration.
VS-1SC: PTT/VOX unit. Required when using these headsets.

EARPHONE

AD-52 SP-13

SP-13: EARPHONE.
AD-52: EARPHONE ADAPTER
Provides clear audio even in noisy environments.

STUBBY ANTENNAS
• FA-SC56V: 150–162MHz
• FA-SC57V: 160–174MHz
• FA-SC73U: 450–490MHz

CUT ANTENNAS
• FA-SC61VC: 136–174MHz
• FA-SC61UC: 380–520MHz
Cut the antenna element to tune to a specific center frequency.

ANTENNAS
• FA-SC25V: 136–150MHz
• FA-SC55V: 150–174MHz
• FA-SC25U: 400–430MHz
• FA-SC57U: 430–470MHz
• FA-SC72U: 470–520MHz

IDAS system digital mode ready

The IDAS (Icom Digital Advanced System) is Icom's digital PMR system using the NXDN™ common air interface. It has useful calling features including selective calling, status message, radio stun/kill/revive, etc with spectrum efficient 6.25kHz channel spacing.

The IC-F3162 series provides 2 optional slots: one optional slot for the UT-126H digital unit and one for an additional option board. See the IDAS brochure for details.

DIGITAL



SPECIFICATIONS

GENERAL

- Frequency range :
IC-F3162T/S 136–174MHz
IC-F4162T/S 400–470MHz
- Number of channels : 512 channels/128 zones
- Channel spacing : 12.5kHz/20kHz/25kHz
6.25kHz (with UT-126H)
- PLL channel step : 2.5kHz, 3.125kHz
- Antenna impedance : 50Ω
- Power supply requirement : 7.2V DC nominal
- Current drain (at 7.2V DC; approx.):
Transmit at 5W/5W 1.5A/1.8A (VHF/UHF)
Receive Stand-by 100mA
150mA (with UT-126H)
Rated output 600mA
- Usable temperature range : –25°C to +55°C
- Dimensions : 53 (W) × 136 (H) × 38.5 (D) mm
(projections are not included)
- Weight (approx.) : 340g (with BP-232N)

TRANSMITTER

- Output power : 5W (VHF), 5W (UHF)
- Max. frequency deviation : ±5.0/4.0/2.5kHz (Wide/middle/narrow)
- Frequency error : ±1.0ppm
- Spurious emissions : 0.25μW (≤1GHz)
1.0μW (>1GHz)
- Adjacent channel power : 70dB min. (Wide, middle)
60dB min. (Narrow)
- Audio harmonic distortion : 3% typ. (AF 1kHz, 40% deviation)
- Modulation limiting : 60–100% of max. deviation
- Ext. microphone connector: 9-pin multi connector/ 2.2kΩ

Measurements made in accordance with EN 300-086.
All stated specifications are subject to change without notice or obligation.

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia and/or other countries. NXDN is a trademark of Icom Incorporated and Kenwood Corporation. LTR is a trademark of E.F. Johnson Company. All other trademarks are the properties of their respective holders.

RECEIVER

- Intermediate frequency : 46.35MHz/2nd 450kHz
- Sensitivity :
FM –4dBμV typ. (emf, at 20dB SINAD)
Digital (with UT-126H) –8dBμV typ. (emf, at 5% BER)
- Squelch sensitivity : –4dBμV typ. (emf, at threshold)
- Adjacent channel selectivity : 75/75/68dB typ. (Wide/middle/narrow)
- Spurious response : 70dB min.
- Intermodulation : 67dB typ.
- Audio output power : 500mW typ.
(at 5% distortion with an 8Ω load)
- External speaker connector: 9-pin multi connector/ 8Ω

Applicable U.S. Military Specifications & IP Rating

Icom makes rugged products that have been tested to and passed the following MIL-STD requirements and Ingress Protection standards.

Standard	MIL 810F	
	Method	Procedure
Low Pressure	500.4	I, II
High Temperature	501.4	I, II
Low Temperature	502.4-3	I, II
Temperature Shock	503.4	I
Solar Radiation	505.4	I
Rain Blowing/Drip	506.4	I, III
Humidity	507.4	–
Salt Fog	509.4	–
Dust Blowing	510.4	I
Vibration	514.5	I
Shock	516.5	I, IV

Also meets equivalent MIL-STD-810-C, -D and -E.

Ingress Protection Standard

Dust & Water IP55 (Dust-protection and water jet resistance)

SUPPLIED ACCESSORIES (May differ according to version)



Icom Inc.

1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.

2380 116th Avenue NE,
Bellevue, WA 98004, U.S.A.
Phone: +1 (425) 454-8155
Fax: +1 (425) 454-1509
E-mail: sales@icomamerica.com
URL: <http://www.icomamerica.com>

Icom Canada

Glenwood Centre #150-6165 Highway 17,
Delta, B.C., V4K 5B8, Canada
Phone: +1 (604) 952-4266
Fax: +1 (604) 952-0090
E-mail: info@icomcanada.com
URL: <http://www.icomcanada.com>

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone: +61 (03) 9549 7500
Fax: +61 (03) 9549 7505
E-mail: sales@icom.net.au
URL: <http://www.icom.net.au>

Icom New Zealand

146A Harris Road, East Tamaki,
Auckland, New Zealand
Phone: +64 (09) 274 4062
Fax: +64 (09) 274 4708
E-mail: inquiries@icom.co.nz
URL: <http://www.icom.co.nz>

Icom (Europe) GmbH

Communication Equipment
Himmelgeister Str. 100,
D-40225 Düsseldorf, Germany
Phone: +49 (0211) 346047
Fax: +49 (0211) 333639
E-mail: info@icom-europe.com
URL: <http://www.icomeurope.com>

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"
Bajos A 08174, Sant Cugat del Valles,
Barcelona, Spain
Phone: +34 (93) 590 26 70
Fax: +34 (93) 589 04 46
E-mail: icom@icomspain.com
URL: <http://www.icomspain.com>

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay,
Kent, CT6 8LD, U.K.
Phone: +44 (01227) 741741
Fax: +44 (01227) 741742
E-mail: info@icomuk.co.uk
URL: <http://www.icomuk.co.uk>

Icom France s.a.s.

Zac de la Plaine,
1 Rue Brindejonc des Moulinais, BP 45804,
31505 Toulouse Cedex 5, France
Phone: +33 (5) 61 36 03 03
Fax: +33 (5) 61 36 03 00
E-mail: icom@icom-france.com
URL: <http://www.icom-france.com>

Icom Polska

81-850 Sopot, ul. 3 Maja 54, Poland
Phone: +48 (58) 550 74 35
Fax: +48 (58) 551 0484
E-mail: icompolksa@icompolksa.com.pl
URL: <http://www.icompolksa.com.pl>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone: +886 (02) 2559 1899
Fax: +886 (02) 2559 1874
E-mail: sales@asia-icom.com
URL: <http://www.asia-icom.com>

Beijing Icom Ltd.

10C07, Long Silver Mansion, No.88,
Yong Ding Road, Haidian District,
Beijing, 100039, China
Phone: +86 (010) 5889 5391/5392/5393
Fax: +86 (010) 5889 5395
E-mail: bjicom@bjicom.com
URL: <http://www.bjicom.com>

Your local distributor/dealer: